

Inverters

180 VA – 1200 VA 230 V/50 Hz and 110 V/60 Hz

www.victronenergy.com



Inverter 12/180

SinusMax – Superior engineering

Developed for professional duty, this range of inverters is suitable for the widest range of applications. The design criteria have been to produce a true sine wave inverter with optimized efficiency but without compromise in performance. Employing hybrid HF technology, the result is a top quality product with compact dimensions, light in weight and capable of supplying power, problem-free, to any load.

Extra start-up power

A unique feature of the SinusMax technology is very high start-up power. Conventional high frequency technology does not offer such extreme performance. These Inverters, however, are well suited to power up difficult loads such as computers and low power electric tools.

To transfer the load to another AC source: the automatic transfer switch

For our lower power models we recommend the use of our Filax Automatic Transfer Switch. The Filax features a very short switchover time (less than 20 milliseconds) so that computers and other electronic equipment will continue to operate without disruption.



**Inverter 12/800
with Schuko socket**

LED diagnosis

Please see manual for a description.

Remote on/off switch

Connector for remote on/off switch available on all models.

DIP switch for 50/60Hz selection (48/350 model only)

Available with different output sockets


Please see pictures below.



**Inverter 12/350
with IEC-320 sockets**



**Inverter 12/180
with Schuko socket**



**Inverter 12/180
with Nema 5-15R sockets**



**Inverter 12/800
with IEC-320 socket**



**Inverter 12/800
with Schuko socket**



**Inverter 12/800
with BS 1363 socket**




**Inverter 12/800
with AN/NZS 3112 socket**



**Inverter 12/800
with Nema 5-15R socket**

Inverter	12 Volt 24 Volt 48 Volt	12/180 Discontinued 24/180 Discontinued	12/350 Discontinued 24/350 Discontinued 48/350 Discontinued	12/800 Discontinued 24/800 Discontinued 48/800 IEC socket only	12/1200 Schuko only 24/1200 Discontinued 48/1200 Discontinued
Cont. AC power at 25 °C (VA) (3)		180	350	800	1200
Cont. power at 25 °C / 40°C (W)		175 / 150	300 / 250	700 / 650	1000 / 900
Peak power (W)		350	700	1600	2400
Output AC voltage / frequency (4)		110 VAC or 230 VAC +/- 3 % 50 Hz or 60 Hz +/- 0.1 %			
Input voltage range (VDC)		10,5 - 15,5 / 21,0 - 31,0 / 42,0 - 62,0		9,2 - 17,3 / 18,4 - 34,0 / 36,8 - 68,0	
Low battery alarm (VDC)		11,0 / 22 / 44		10,9 / 21,8 / 43,6	
Low battery shut down (VDC)		10,5 / 21 / 42		9,2 / 18,4 / 36,8	
Low battery auto recovery (VDC)		12,5 / 25 / 50		12,5 / 25 / 50	
Max. efficiency (%)		87 / 88	89 / 89 / 90	91 / 93 / 94	92 / 94 / 94
Zero load power (W)		2,6 / 3,8	3,1 / 5,0 / 6,0	6 / 5 / 4	6 / 5 / 6
Zero load power in search mode		n. a.	n. a.	2	2
Protection (2)		a - e			
Operating temperature range		-40 to +50 °C (fan assisted cooling)			
Humidity (non-condensing)		max 95 %			
ENCLOSURE					
Material & Colour		aluminium (blue Ral 5012)			
Battery-connection		1)	1)	1)	1)
Standard AC outlets		230V: IEC-320 (IEC-320 plug included), CEE 7/4 (Schuko) 120V: Nema 5-15R (12/1200 only)			
Protection category		IP 20			
Weight (kg / lbs)		2.7 / 5.4	3.5 / 7.7	6.5 / 14.3	8.5 / 18.7
Dimensions (hxwx d in mm) (hxwx d in inches)		72x132x200 2.8x5.2x7.9	72x155x237 2.8x6.1x9.3	104 x 194 x 305 4.1 x 7.6 x 12.0	104 x 194 x 305 4.1 x 7.6 x 12.0
ACCESSORIES					
Remote on-off switch		Two pole connector			
Automatic transfer switch		Filax			
STANDARDS					
Safety		EN 60335-1			
Emission Immunity		EN 55014-1 / EN 55014-2/ EN 61000-6-2 / EN 61000-6-3			
1) Battery cables of 1.5 meter (12/180 with cigarette plug) 2) Protection key: a) output short circuit b) overload c) battery voltage too high d) battery voltage too low e) temperature too high		3) Non-linear load, crest factor 3:1 4) Frequency can be set by DIP switch (48/350 model only)			



Battery Alarm

An excessively high or low battery voltage is indicated by an audible and visual alarm, and a relay for remote signalling.



BMV-700 Battery Monitor

The BMV-700 Battery Monitor features an advanced microprocessor control system combined with high resolution measuring systems for battery voltage and charge/discharge current. Besides this, the software includes complex calculation algorithms to exactly determine the state of charge of the battery. The BMV-700 selectively displays battery voltage, current, consumed Ah or time to go. The monitor also stores a host of data regarding performance and use of the battery.